

## ISN-SM Seismic Detectors



The following models belong to the ISN-SM series seismic detectors:

Model	Features
ISN-SM-50	<ul style="list-style-type: none"> <li>• 4 m operating radius on concrete</li> <li>• 50 m<sup>2</sup> monitoring area</li> </ul>
ISN-SM-80	<ul style="list-style-type: none"> <li>• 5 m operating radius on concrete</li> <li>• 80 m<sup>2</sup> monitoring area</li> </ul>

Each seismic detector monitors objects and surfaces, has a low-profile design, and can be installed effortlessly, even in tight spaces. ISN-SM seismic detectors are designed to monitor safes, night safes, and automatic teller machines.

### System overview

When cutting and drilling through materials such as concrete, steel, or synthetic reinforcements, deviations from the structures' normal vibration pattern ensue. The SENSTEC sensor converts vibration deviations into electrical signals. The digital processing in the seismic detector analyzes the signals and compares them to a frequency range typical of tools used to break into safes, night safes etc. If the signals fall within this frequency range, the seismic detector transmits an alarm via a relay contact.

- ▶ 24-hour surveillance of vault walls and doors, safes, night safes, and automatic teller machines
- ▶ Sensitivity settings using DIP switches
- ▶ SENSTEC® sensor and signal processing system based on microcontrollers
- ▶ Low profile design

### Functions

#### Detection

The seismic detector recognizes vibrations caused by explosives and tools such as diamond-tipped drills, mechanical and hydraulic rams, flame cutters, thermal lances, or water jet cutters.

The SENSTEC sensor and the digital signal processing monitor a narrow frequency range, thus offering reliable detection. The seismic detector tolerates environmental conditions such as air movement and noise.

#### Sensitivity settings using DIP switches

The sensitivity settings are selected using DIP switch settings. Select the appropriate sensitivity setting for the application, the material, and the object, as well as any interference present. The following settings are available:

- Steel, 2.0 m
- Steel, 2.5 m
- Concrete, 4.0 m
- User mode, with SensTool

#### SensTool software

SensTool software for PCs provides the following options:

- Changing factory default settings
- Monitoring detector performance
- Storing information such as integrator signals
- Selecting additional settings for detector and shock sensitivity

### Fixing device

A fixing device is available as an optional hardware accessory for ISN-SM seismic detectors. When the system is armed, the fixing device monitors safes and strong rooms for attacks using thermal and mechanical tools, as well as unauthorized opening. The fixing device components consist of a detector plate, a door plate, and a standby plate.

The detector plate has a monitoring microswitch and a magnetic contact. When the system is armed, the monitoring switch in the detector plate is closed. If the detector is removed from the door plate, the monitoring switch opens and triggers an alarm. The detector can be hung on the standby plate during working hours.

### Swivel plate

A swivel plate is available as an optional hardware accessory for the ISN-SM seismic detector. A swivel plate is used for monitoring safes and strong rooms with exposed keyholes. A microswitch in the swivel plate monitors movement. Any unauthorized swivel movement immediately triggers an alarm. When the system is armed, the swivel plate fully covers the keyhole. When the system is disarmed, the swivel plate swivels so it is at a 90° angle to the keyhole.

### Regulatory information

Region	Regulatory compliance/quality marks	
Europe	CE	2014/30/EU (EMC) 2011/65/EU (RoHS)
	CE	EN 61000-6-3:2007/A1:2011; EN 50130-4:2011 [ISN-SM-30, ISN-SM-50]
USA	FCC	S0072FCC [GM710, GM730, GM760, GMXS1, ISN-SM-30, ISN-SM-50, ISN-SM-80, ISN-GMX-S1]
	UL	ANSR BP1448 - Intrusion Detection Units [ISN-SM-50, ISN-SM-80]
Canada	ULC	ANSR7 BP1448 – Intrusion Detection Units Certified for Canada
China	CSP	CSP2011031901000203
Germany	VdS	G106071 [ISN-SM-50]
	VdS	G106072 [ISN-SM-80]
the Netherlands	NCP	06229520/AA/00 [ISN-SM-50]
Russia	GOST	TC N RU Д-НЛ.МН09.В.00334 EAC

### Installation/configuration notes

#### Installation notes

Seismic detectors can be mounted directly onto steel plates with smooth surfaces. The surface must not be painted and must be level with a maximum deviation of 0.1 mm. If these conditions cannot be met, the MXPO mounting plate must be used.

The seismic detector cannot be mounted directly onto plastered or unplastered concrete.

### Technical specifications

#### Electromagnetic sensitivity

Compatibility:	Better than EN 50130-4
HF interference tolerance (EN 61000-4-3):	No alarm or setup at critical frequencies within a range of 1 MHz to 1000 MHz at > 30 V/m.

#### Housing

Dimensions:	8.9 cm x 8.9 cm x 2.2 cm
Weight:	0.320 kg

#### Environmental conditions

Humidity (EN60721):	Up to 95% relative humidity, not condensing
Housing protection class (EN 60529, EN 50102):	IP43
Temperature (operating):	-40 °C to +70 °C
Temperature (storage):	-50 °C to +70 °C

#### Function test

For the test:	Low < 1.5 VDC High > 3.5 VDC
Test duration (including test transmitter ISN-GMX-S1):	≤ 3 sec

#### Operating radius according to monitoring area on concrete and steel for all tools, including thermal tools

Model	Operating radius		Monitoring area
	Concrete	Steel	Concrete
ISN-SM-50	4 m	2 m	50 m <sup>2</sup>
ISN-SM-80	5 m	2,5 m	80 m <sup>2</sup>

## Outputs

Alarm relay (changeover contact):	Contact closed in standby mode (opened in the event of an alarm) designed for 30 VDC, 100 mA, resistance < 20 Ohm
Alarm holding time:	Approx. 2.5 sec
Tamper switch/wall tamper:	Tamper contact closed in standby mode (opened in the event of tampering) designed for 30 VDC, 100 mA, resistance < 45 Ohm
Test connection:	Analog integration signal

## Power requirements

Power consumption at 12 VDC:	Alarm: 6 mA
	Standby: 3 mA
Power supply monitoring:	8 VDC to 16 VDC (12 V nominal)
	Alarm: < 7 VDC

## Input for remote controlled reduction of sensitivity

For reduction:	Low < 1.5 VDC
	High > 3.5 VDC
Reduction to:	1/8 of current setting

## Trademarks

SENSTEC® is a registered trademark of Siemens Building Technologies.

## Ordering information

### ISN-SM-50 Seismic detector, 50m<sup>2</sup>

Seismic detector with 4m operating radius on concrete and 50m<sup>2</sup> monitoring area.

Order number **ISN-SM-50 | F.01U.002.248**

### ISN-SM-80 Seismic detector, 80m<sup>2</sup>

Seismic detector with 5m operating radius on concrete and 80m<sup>2</sup> monitoring area.

Order number **ISN-SM-80 | F.01U.002.246**

## Accessories

### ISN-GMX-D7 Anti-drill foil

Anti drill protection foil for use in seismic detectors.

Order number **ISN-GMX-D7 | F.01U.004.305**

### ISN-GMX-P0 LSN seismic detector, mounting plate

Mounting plate for seismic detectors. Suitable for mounting seismic detectors to steel or concrete surfaces.

Order number **ISN-GMX-P0 | F.01U.003.366**

### ISN-GMX-P3S LSN seismic detector, swivel plate

Swivel plate for use with ISN-SM-50 seismic detectors.

Order number **ISN-GMX-P3S | F.01U.003.368**

### ISN-GMX-PZ Swivel plate for ISN-SM-80

Swivel plate for use with ISN-SM-80 seismic detectors.

Order number **ISN-GMX-PZ | F.01U.003.370**

### ISN-GMX-S1 Seismic detector, test transmitter

Test transmitter for installation under a seismic detector. Checks the detector and the physical contact between the detector and the protected object.

Order number **ISN-GMX-S1 | F.01U.003.371**

### ISN-GMX-W0 Wall-recess kit

Wall recess set for surface or flush mounting a seismic detector to a wall.

Order number **ISN-GMX-W0 | F.01U.003.372**

### ISN-GMX-P3S2 Spacer (2mm)

Spacer 2mm thick for swivel plate.

Order number **ISN-GMX-P3S2 | F.01U.003.367**

## Software Options

### ISN-SMS-W7 Sensor tool PC software

Cable connecting the PC to the detector.

Order number **ISN-SMS-W7 | F.01U.004.306**

## Services

### EWE-SEISMIC-IW 12 mths wrty ext Seismic detector

12 months warranty extension

Order number **EWE-SEISMIC-IW**

## Represented by:

**Europe, Middle East, Africa:**  
Bosch Security Systems B.V.  
P.O. Box 80002  
5600 JB Eindhoven, The Netherlands  
[www.boschsecurity.com/xc/en/contact/](http://www.boschsecurity.com/xc/en/contact/)  
[www.boschsecurity.com](http://www.boschsecurity.com)

**Germany:**  
Bosch Sicherheitssysteme GmbH  
Robert-Bosch-Platz 1  
D-70839 Gerlingen  
[www.boschsecurity.com](http://www.boschsecurity.com)

**North America:**  
Bosch Security Systems, LLC  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
[www.boschsecurity.com](http://www.boschsecurity.com)

**Asia-Pacific:**  
Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
[www.boschsecurity.com/xc/en/contact/](http://www.boschsecurity.com/xc/en/contact/)  
[www.boschsecurity.com](http://www.boschsecurity.com)