

# Plena All-in-One Call Station

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Stylish, high-quality six-zone Call Station for the Plena All-in-One System
- ▶ Six-zone selection keys with LED indicators, and an 'all-call' key
- ▶ Momentary Press To Talk (PTT) key
- ▶ Configurable gain, speech filter, limiter, and output level for improved intelligibility
- ▶ Configurable attention chime

The Plena All-in-One Call Station is a stylish, high-quality call station that comprises a stable metal base, a flexible microphone stem, and a unidirectional condenser microphone. It has six zone keys and a separate all-call key for easy selection of zones in a Plena All-in-One public address system. A large 'Press To Talk' (PTT) key, with re-dial function, is used to control the call.

In addition to tabletop use, the special design allows the Call Station to be neatly flush-mounted in a desktop. Up to six Call Stations can be connected in a loop-through arrangement to the same All-in-One Unit, with configurable priority.

## Functions

The Call Station supports the selection of six zones and has selectable gain, a selectable speech filter, and a limiter for improved intelligibility. The Call Station has a balanced line-level output, which means it can be positioned up to 600 meters from the Plena All-in-One Unit, by using a Cat-5 cable.

Built-in programming modes are used to select the speech filter, the microphone gain settings, and the Call Station ID. A concealed rotary control at the base

of the Call Station is used to set the output level attenuation. LEDs on the Call Station show which zones have been selected.

An additional LED gives visible feedback on the active state of the microphone and the system:

- Green flashing indicates that the system is in standby (a chime is sounded)
- Green indicates that the microphone is active
- Amber indicates that the system is occupied by another higher priority call

## Controls and indicators

- Power on LED
- Press To Talk (PTT) key
- PTT status LED
- Six zone selection keys
- Six zone selection LEDs
- All-call key
- Concealed rotary volume control

## Interconnections

- RJ45 system connector
- RJ45 loop-through connector

### Certifications and approvals

Safety	IEC/EN 60065
EMC	EN 55103-1 EN 55103-2 EN 61000-3-2 EN 61000-3-3
Environment	EN 50581
US	UL 60065 FCC Part 15B
CA	CSA C22.2.60065
CN	CCC
AU/NZ	C-Tick

Region	Certification
Europe	CE

### Parts included

Quantity	Component
1	All-in-One Call Station
1 m	Cat-5 cable with RJ45 plugs
1	Terminator plug

### Technical specifications

#### Electrical

Power Supply	
Voltage	24 Vdc (24 Vdc supplied by PLN-6AIO240)
Current consumption	<50 mA
Performance	
Nominal acoustic sensitivity	85 dB SPL @ 1 kHz (gain preset 0 dB)
Nominal output level	1 V
Input sound level (max.)	110 dB SPL
Gain preset	
Limiter threshold	1 V
Compression ratio limiter	1:20
Distortion	<2% (maximum input)
Input noise level (equiv.)	25 dBA SPL
Frequency response	100 Hz to 14 kHz +/-6 dB
Speech filter	-3dB @ 315 Hz, high-pass, 6 dB/oct
Output impedance	200 ohm

Selections	
Chimes	1-, 2- or 4-tone chime selected on Call Station

#### Mechanical

Base dimensions (H x W x D)	55 x 108 x 240 mm (1.57 x 3.97 x 9.25 in)
Weight	Approx. 0.5 kg (1.1 lb)
Mounting	Tabletop
Color	Charcoal with silver
Stem length with microphone	390 mm (15.35 in)
Connection	2 x RJ45, Cat-5, max. length 600 m

#### Environmental

Operating temperature	-10°C to +45°C (14°F to +113°F)
Storage temperature	-40°C to +70°C (-40°F to +158°F)
Relative humidity	<95% (non-condensing)

### Ordering information

#### Plena All-in-One Call Station

Call station for six zones with unidirectional microphone and attention chimes.

Order number **PLN-6CS**

**Represented by:**

**Americas:**

Bosch Security Systems, Inc.  
12000 Portland Avenue South  
Burnsville MN 55337, USA  
Phone: +1-800-392-3497  
Fax: +1-800-955-6831  
audiosupport@us.bosch.com  
www.boschsecurity.com

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security  
Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com